

T2N/1S Emergency Output Chart

| Load Voltage | Em Wattage (EOF Watts) | Em Current (EOF Milliamp) |
|--------------|------------------------|---------------------------|
| 50 | 2.31 | 46 |
| 55 | 2.32 | 42 |
| 60 | 2.32 | 39 |
| 65 | 2.33 | 36 |
| 70 | 2.34 | 33 |
| 75 | 2.34 | 31 |
| 80 | 2.35 | 29 |
| 85 | 2.35 | 28 |
| 90 | 2.35 | 26 |
| 95 | 2.35 | 25 |
| 100 | 2.35 | 24 |
| 105 | 2.35 | 22 |
| 110 | 2.35 | 21 |
| 115 | 2.35 | 20 |
| 120 | 2.35 | 20 |
| 125 | 2.35 | 19 |
| 130 | 2.35 | 18 |
| 135 | 2.35 | 17 |
| 140 | 2.35 | 17 |
| 145 | 2.35 | 16 |
| 150 | 2.34 | 16 |
| 155 | 2.34 | 15 |
| 160 | 2.33 | 15 |
| 165 | 2.33 | 14 |
| 170 | 2.32 | 14 |
| 175 | 2.32 | 13 |
| 180 | 2.31 | 13 |
| 185 | 2.31 | 12 |
| 190 | 2.30 | 12 |
| 195 | 2.30 | 12 |
| 200 | 2.29 | 11 |
| 205 | 2.29 | 11 |
| 210 | 2.28 | 11 |
| 215 | 2.28 | 11 |
| 220 | 2.27 | 10 |
| 225 | 2.27 | 10 |
| 230 | 2.26 | 10 |
| 235 | 2.26 | 10 |
| 240 | 2.25 | 9 |
| 245 | 2.25 | 9 |
| 250 | 2.24 | 9 |
| 255 | 2.24 | 9 |
| 260 | 2.23 | 9 |
| 265 | 2.23 | 8 |
| 270 | 2.22 | 8 |
| 275 | 2.22 | 8 |
| 280 | 2.21 | 8 |
| 285 | 2.21 | 8 |
| 290 | 2.20 | 8 |
| 295 | 2.20 | 7 |
| 300 | 2.19 | 7 |