



The MMB/NC/10 is supplied as a split remote conversion kit for mounting away from the fitting. It is suitable for 230V DC Loads.

- Conversion Kit for Mains Voltage Lamps
- Deep discharge protection
- Split Pack Arrangement for Ceiling Voids
- High Temperature NiCd Batteries
- Converts Loads Up To 10W
- Passes Through 57mm Aperture

A split pack, 3 hour remote conversion kit for 230V DC loads. This pack will power the load at 100% (BLF*) for three hours in emergency.

The pack will power Up To 10W of load.

* BLF = Ballast Lumen Factor/the percentage output in emergency

Order Codes

MMB/NC/10	Maintained Pack for 230V DC Loads up to 10W
CRL5	White, ceiling recess charge LED holder

* Please ensure that your lamp/luminaire is capable of being powered by DC

Technical Details:

Input Voltage	230-240 Volts AC 50/60 Hz
Input Current	Non-Maintained - 38mA $\lambda = 0.84$
Battery Type	12V 4.0Ah NiCd in Self-Extinguishing Sleeve
Enclosure Dimensions	228mm L x 41mm W x 35mm H
Battery Dimensions	850mm L x 35mm Φ
Overall Weight	2.0Kg
Ingress Protection	IP20
Recharge Time	24 Hours